

# TM - NEMA CONTROL

## AC Reversing Starters



**B**

### AC Reversing Starters - Bulletin 6030 TM

NEMA Size	Maximum Motor <sup>2</sup> Horsepower Rating			Open Type
	200V	230V	460-575V	
00	1½	1½	2	T30U03A -*
0	3	3	5	T30U030 -*
1	7½	7½	10	T30U031 -*
2	10	15	25	T30U032 -*
4	40	50	100	T30U034 -*
5	75	100	200	
6	150	200	400	

See Vacuum Contactors in Section A

**Notes:**

1. Includes starter complete with one N.O. contact on each contactor and 3 phase overload relay less heaters. All starters are mechanically and electrically interlocked.
2. For plug-stop or jogging duty or where operations exceed 5 per minute, starter sizes should be chosen in accordance with NEMA Standard ICS 2-321-3, as listed in table.
3. For Ambient Compensated overload see B37.

### Plug-Stop or Jogging Duty NEMA ICS 2-321-3

NEMA Size	Horsepower Ratings - Three Phase, 60Hz			
	200V 60 Hz	230V 60 Hz	380V 50 Hz	460/575V 60 Hz
0	1½	1½	1½	2
1	3	3	5	5
2	7½	7½	15	15
3	15	15	30	30
4	25	30	50	60
5	60	75	125	150
6	125	10\50	250	300

### Ordering Information

- Use complete catalog number when ordering. Replace the (\*) with the suffix from the coil table.
- Engineering Data page B26.
- Modifications page B18.
- Heater Tables page B15.
- Renewal Parts page B21.
- Dimensions page B22.

Coil Volt/Hertz	Suffix
24/60 or 24/50	-96
110-120/60 or 110/50	-76
220-240/60 or 220/50	-26
440-480/60 or 440/50	-46
550-600/60 or 550/50	-56
200-208/60	-86